



## Porodo 4\*PD 4\*QC Multi-Functional Magsafe Fast Charger

SKU: PD-MFMGFC

Thank you for choosing our multifunctional wireless charger. Please read the following information carefully to ensure proper use and reference for future use.

## Features

1. This device features 4 Power Delivery (PD) ports, 4 Quick Charge 3.0 (QC 3.0) ports, and wireless charging, totaling 9 charging ports. It can deliver a combined maximum power of 110W. Should the power exceed 110W, the device will cease operation to prevent damage.
2. For individual port specifications: each QC 3.0 port can output 18W, and the PD port can output a maximum of 45W for USB 5, 30W for USB 6, 20W for USB 7, and 20W for USB 8.
3. When USB 1 and USB 5 are used simultaneously, their combined output is 18W + 30W. Similarly, when USB 2 and USB 6, USB 3 and USB 7, USB 4 and USB 8 are used concurrently, they support a combined output of 5A+5V/1.5A.
4. A smart sleep switch is integrated to automatically dim the display after two minutes of inactivity. Features such as vibration, voice control, and a gentle light touch can reactivate the display screen without causing disturbance, facilitating nighttime use.
5. The current display screen provides real-time monitoring of the current and voltage for each charging port.
6. The charger is built with an intelligent protection system that includes safeguards against over-voltage, overload, and over-current, ensuring the device's operation is stable and safe, thereby effectively preventing accidents.

# Specification

|                               |  |
|-------------------------------|--|
| Model                         | PD-MFMGFC                                    |
| Interface type                | USB-a*4, USB-c*4                             |
| Input                         | AC100 - 240V (50 - 60Hz)                     |
| USB-1[QC3.0] output           | 5V/3A - 9V/2A - 12V/1.5A                     |
| USB-5[PD] output              | 5V/3A - 9V/3A - 12V/3A - 15V/3A - 20V/2.25A  |
| USB-1[QC3.0]+USB-5[PD] output | 18W+30W                                      |
| USB-2[QC3.0] output           | 5V/3A - 9V/2A - 12V/1.5A                     |
| USB-6[PD] output              | 5V/3A - 9V/3A - 12V/2.5A - 15V/2A - 20V/1.5A |
| USB-2[QC3.0]+USB-6[PD] output | 5V/1.5A + 5V/1.5A                            |
| USB-3[QC3.0] output           | 5V/3A - 9V/2A - 12V/1.5A                     |
| USB-7[PD] output              | 5V/3A - 9V/2.22A - 12V/1.67A                 |
| USB-3[QC3.0]+USB-7[PD] output | 5V/1.5A + 5V/1.5A                            |
| USB output                    | 5V/3A - 9V/2A - 12V/1.5A                     |
| USB-8[PD] output              | 5V/3A - 9V/2.22A - 12V/1.67A                 |
| USB-4[QC3.0]+USB-8[PD] output | 5V/1.5A + 5V/1.5A                            |
| Wireless output               | 15W  |
| Total power                   | 110W (max)                                   |
| Power cord length             | 1.2m   |
| Bare metal size               | 45×80×110 mm                                 |

## Charging Guideline

1. Always use the standard power cord and the charging cable initially provided with your smartphone to ensure compatibility and optimal charging.
2. For wireless charging, position the phone at the center of the charging pad to align with the induction area. A magnetic rubber ring aids in proper alignment. The thickness of any case or cover on your phone should not exceed 2mm to ensure charging efficiency.

3. The Quick Charge (QC) port and the Power Delivery (PD) port are designed to function on separate circuits. Utilizing both ports simultaneously may result in lower power output or reduced charging voltage. For the fastest charging experience, it is advisable to use one port at a time.

## Precautions

1. The charger has a maximum power output of 110W and is capable of charging multiple devices concurrently. Each device draws a different current level. If the total power draw exceeds 110W, the charger will enter an overcurrent protection mode (indicated by the screen flashing), and it will cease to function to prevent damage. In such an event, promptly decrease the number of devices being charged to reduce the load. After disconnecting the charger from the power source for approximately 10-5 minutes, it will reset, allowing you to resume normal operation.
2. Do not disassemble the charger, submerge it in water, expose it to high-temperature environments, or place it in fire.
3. Avoid applying any external force that may cause damage to the equipment.
4. It is a normal occurrence for the charger to emit a certain amount of heat during use.

## Product Schematic

1. Magnetic Wireless Charging
2. Displays Voltage and Current Output
3. Overload Alarm Notification
4. Operating Instructions
5. Fast Charging Indicator
6. Displays Active Ports





- 7 . Corresponding Active Output Ports
- 8 . ABS + PC Fire-Resistant Material
- 9 . PD45W and QC3.0 Dedicated Output Port
- 10. PD30W and QC3.0 Exclusive Output Port
- 11 . PD20W and QC3.0 Designated Output Port
- 12. PD20W and QC3.0 Specific Output Port

## Warranty

Products that you buy directly from our **Porodo** website or shop come with a 24-month warranty.

When you buy **Porodo** products from any of our approved sellers, you only get a 12-month warranty. If you want to extend this warranty, go to our website at **<https://porodo.net/warranty>** and fill out the form with your information. Don't forget to upload a picture of the product too. After we've checked and accepted your request, we'll send you an email to confirm that your product's warranty has been extended.

For more info, please check:  
**[porodo.net/warranty](https://porodo.net/warranty)**

## Contact Us

If you have any questions about this Privacy Policy, please contact us at:  
**[info@porodo.net](mailto:info@porodo.net)**

Website: **[porodo.net](https://porodo.net)**

Service Support: **[support@porodo.net](mailto:support@porodo.net)**

Instagram: **[porodo](https://www.instagram.com/porodo)**