



Powerology

KICKVOLT Portable Charging Stand Power Bank

SKU: PWM11QI2BK

Table of Contents

Product Overview	2
Specifications	3
Charging Devices	3
Recharge the Power Bank	4
Simultaneous Charging	4
Important Notes	5
Safety Instructions	5
Disposal	6
Warranty	7
Contact Us	7

Product Overview



- 1. MagSafe Compatible Wireless Charging for Phone
- 2. Wireless Charging for AirPods
- 3. Wireless Charging for Apple Watch
- 4. Power Button
- 5. Power Indicators

Specifications

Model	PWM11QI2
Battery Capacity	10000mAh
USB-C Input	5V/3A, 9V/2.22A, 12V/1.5A, 20W Max
USB-C Output	5V/3A, 9V/2.22A, 12V/1.5A, 20W Max
USB-A Output	5V/3A, 9V/2.22A, 10V/2.25A, 12V/1.5A, 22.5W Max
Wireless Phone Output	15W Max
Wireless Earbuds Output	5W Max
Wireless Watch Output	2.5W Max
Product Size	24 x 68 x 120mm
Product Weight	285g

Charging Devices

On-the-Go Charging Mode

1. Power on the device by turning on the power bank.
2. Attach the power bank to your phone (compatible with iPhone 16-12 Series or newer).



Multiple-Charging Mode

1. Unfold the stand to the appropriate angle.
2. Press the power button to turn on the power bank.
3. Place the devices in their designated charging areas.



Recharge the Power Bank



The power bank can be recharged using a USB-C cable and adapter. While charging, the indicators will display the current power status.

Simultaneous Charging



You can charge your iPhone, Apple Watch, AirPods, and power bank simultaneously by using a single charging cable.

1. Connect the power bank to a USB-C adapter.
2. Place the iPhone, AirPods, and Apple Watch in their designated charging areas.

Important Notes

1. This wireless charger is not compatible with non-MagSafe phone cases.
2. Do not use an adapter with an output lower than 5V/2A (10W).
3. Wireless chargers offer more convenience than wired chargers but are limited by current wireless technology, resulting in a slower charging speed compared to wired chargers.
4. High temperatures can reduce charging speed and limit power output, which is common for all wireless chargers. It is recommended to charge your device in environments with temperatures below 25°C/77°F.
5. Both the protective phone case and the positioning of your device on the wireless charger can affect charging speed. The farther your device is from the center of the charger, the slower the charging speed will be.

Safety Instructions

When using this power bank, please follow the basic safety precautions listed below:

1. Store the power bank in a cool, dry place.
2. Avoid storing the power bank in hot or humid environments.
3. Do not use a power supply or charger that is not recommended or approved by the manufacturer, as this may pose a fire or injury risk.
4. The operating temperature for the power bank should be between 0°C to 40°C (32°F to 104°F).

- 5.** Do not attempt to disassemble the power bank. If service or repair is necessary, please contact a qualified service provider. Incorrect reassembly may cause fire or injury.
- 6.** If the power bank is not used for an extended period, it is advisable to charge and discharge it once every three months to maintain battery health.
- 7.** When charging a device, the power bank may feel warm. This is normal and should not be a cause for concern.
- 8.** Over time, the battery performance may decline under normal use.
- 9.** Do not dispose of the power bank in fire or high heat, as this may cause hazardous conditions.
- 10.** Do not clean the power bank with harsh chemicals or detergents, as this may damage the surface and functionality.
- 11.** Misuse, dropping, or excessive force may result in damage to the power bank.
- 12.** When disposing of the power bank or its battery, ensure cells or batteries with different electrochemical systems are kept separate from each other.

Disposal

This product must not be disposed of as unsorted household waste. It is important to separate such waste for proper treatment and recycling, in compliance with local waste management regulations.

Warranty

Products that you buy directly from our **Powerology** website or shop come with a 24-month warranty.

The 24-month warranty applies to products purchased directly from our **Powerology** website or store. If **Powerology** products are bought from any of our verified retailers, then the product is eligible for only a 12-month warranty. To extend your product's warranty, visit our website **powerology.me/warranty** and fill in your details in the provided form along with an uploaded picture of the product to process your request. Once approved, you will receive a confirmation email of the extended product warranty. Upload the required information within 48 hours of purchase to be eligible for a 24-month warranty period.

For more info, please check:
powerology.me/warranty

Contact Us

If you have any questions about this Privacy Policy, please contact us at: **hey@powerology.me**

Website: **powerology.me**

Instagram: **[powerology_official](https://www.instagram.com/powerology_official)**

Facebook: **[powerology.ME](https://www.facebook.com/powerology.ME)**