



Green Lion

Mono MagSafe 10000mAh Power Bank

SKU: GNMPB10KTC

Table of Contents

Product Overview	2
Specifications	2
Product Features	3
Instructions for Use	4
Cleaning and Maintenance	5
Safety Precautions	6
FCC Statement	6
Disposal	7
Warranty	8
Contact Us	8

Product Overview

The Green Lion Monaco MagSafe Power Bank offers a 10,000mAh capacity for reliable on-the-go charging. It supports 15W wireless charging and features strong magnetic attachment for stable use. The built-in LCD indicator displays the remaining power, while the integrated Type-C cable and PD 20W fast charging ensure efficient charging for your devices.

Specifications

Battery Capacity	10,000mAh
Battery Type	Lithium Polymer Cell
USB Output	5V/2.4A (12W Max)
Type-C Input	5V/3A, 9V/2A, 12V/1.5A
Type-C Output	5V/3A, 9V/2.22A, 12V/1.67A
Type-C Cable Output	5V/3A, 9V/2A, 12V/1.5A
Wireless Output	15W (Max)
Material	ABS+PC
Net Weight	179g

Dimensions	28 × 71 × 98mm
Executive Standard	GB/T35590-2017

Product Features

- a.** 10,000mAh Battery Capacity: Provides enough power to charge most devices multiple times before needing a recharge.
- b.** 15W Wireless Charging: Allows cable-free charging for compatible devices with a fast 15W wireless output.
- c.** Magnetic Attachment: Ensures secure attachment to your device for stable and efficient wireless charging.
- d.** USB Output (5V/2.4A, 12W Max): Offers a 12W USB output for fast wired charging of phones and other USB-powered devices.
- e.** USB-C Input & Output (Fast Charging Support): Supports fast charging with USB-C for both input and output, allowing quicker recharges and device charging.
- f.** Integrated Type-C Cable: Comes with a built-in Type-C cable for easy and convenient charging without the need for extra cables.
- g.** LCD Power Indicator: Displays the remaining battery level, so you always know when to recharge the power bank.
- h.** Durable ABS+PC Material: Built with durable materials that ensure strength and portability, making it ideal for everyday use.
- i.** Compact and Lightweight Design: Small and lightweight, perfect for carrying on the go without adding bulk.

Instructions for Use

1. Charging the Power Bank:

- 1.1. To charge the power bank, connect the included Type-C cable to the power bank's USB-C input port.
- 1.2. Plug the other end of the cable into a compatible charger or USB power source.
- 1.3. The LCD indicator will show the charging status. Once fully charged, the power bank is ready for use.

2. Charging Your Device Wirelessly:

- 2.1. Place your compatible device on the magnetic surface of the power bank, ensuring it is aligned for stable wireless charging.
- 2.2. The power bank will begin charging your device without the need for any cables.
- 2.3. For devices with magnetic charging support, the power bank will securely attach for optimal performance.

3. Charging Your Device via USB:

- 3.1. Connect your device to the power bank using a compatible USB cable.
- 3.2. The power bank will automatically begin charging your device once connected.

4. Monitoring Battery Level:

Check the LCD display to see the remaining battery level of the power bank. This will help you know when it's time to recharge.

5. Recharging the Power Bank:

When the battery level of the power bank is low, recharge it using the Type-C input port. The power bank can be recharged quickly using a compatible USB-C charger.

6. Storage:

Store the power bank in a cool, dry place when not in use. Ensure it is not exposed to extreme temperatures or moisture.

Cleaning and Maintenance

1. To maintain the performance and longevity of your Green Lion Monaco MagSafe Power Bank, please follow these cleaning and maintenance tips:

2. **Cleaning the Surface:** Use a soft, dry cloth to clean the power bank. Avoid using abrasive materials that may scratch or damage the surface.

3. **Avoid Liquids:** Do not use water or any cleaning liquids directly on the power bank. If necessary, slightly dampen the cloth with water and wipe the surface gently.

4. **Charging Ports:** Regularly inspect the charging ports for dust or debris. Use a dry, soft brush or compressed air to carefully clean the ports if needed.

5. **Battery Care:** To maintain battery health, avoid letting the power bank completely discharge frequently. Recharge it when the battery level drops to around 20-30%.

6. **Storage:** When not in use for extended periods, store the power bank in a cool, dry place, and charge it to about 50% every 3-6 months to preserve battery life.

Safety Precautions

1. To ensure safe use of the Green Lion Monaco MagSafe Power Bank, please follow these guidelines:
2. **Avoid Overheating:** Do not expose the power bank to extreme temperatures, such as direct sunlight or heat sources, to prevent overheating or damage.
3. **Proper Charging:** Use only the recommended cables and chargers for charging the power bank. Avoid using damaged or frayed cables.
4. **Water and Moisture:** Keep the power bank dry and avoid using it in wet or humid environments.
5. **Handling:** Do not drop or subject the power bank to impact. Mishandling may cause damage or malfunction.
6. **Storage:** Store the power bank in a cool, dry place when not in use. Ensure it is not placed near flammable materials.
7. **Avoid Short Circuits:** Do not connect the power bank's output directly to any metal object, which may cause a short circuit.
8. **Overcharging:** While the power bank has built-in protection, it is recommended to unplug it once fully charged to preserve battery life.

FCC Statement

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
 - (1) This device may not cause harmful interference; and
 - (2) This device must accept any interference received, including interference that may cause undesired operation.
2. Changes or modifications not expressly approved by the party

responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.

- Connect the equipment to an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for assistance.

RF warning statement:

The device has been evaluated to meet general RF exposure requirements. The device can be used in portable exposure conditions without restriction.

Disposal

This product must not be disposed of as unsorted household waste. It is important to separate such waste for proper treatment and recycling, in compliance with local waste management regulations.

Warranty

Products that you buy directly from our **Green Lion** website or shop come with a 24-month warranty.

When you buy **Green Lion** products from any of our approved sellers, you only get a 12-month warranty. If you want to extend this warranty, go to our website at **<https://www.greenlion.net/warranty>** and fill out the form with your information. Don't forget to upload a picture of the product too. After we've checked and accepted your request, we'll send you an email to confirm that your product's warranty has been extended.

For more info, please check:

<https://www.greenlion.net/warranty>

Contact Us

If you have any questions about this Privacy Policy, please contact us at:

Website: **<https://www.greenlion.net/>**

Sales: **sales@greenlion.net**

Service Support: **Support@greenlion.net**

Telegram: **[@greenlion_global](https://t.me/greenlion_global)**

Instagram: **[@greenlion_global](https://www.instagram.com/greenlion_global)**