

# PORODO



## **Porodo** **TerraCharge** **65W GaN Dual-Port Adapter**

SKU: PDFWCH087WH

# Table of Contents

Product Overview	2
Specifications	2
Key Features	2
Usage Instructions	3
Safety Precautions	4
Disposal	5
Warranty	6
Contact Us	6

## Product Overview

The Porodo TerraCharge 65W GaN Dual-Port Adapter is a high-performance charging solution that combines advanced Gallium Nitride (GaN) technology for faster, more efficient power conversion with minimal heat generation. This adapter is designed for global use, featuring interchangeable US, UK, and EU plugs, making it an ideal companion for travelers. With a 65W power output and dual USB ports, it allows you to charge two devices simultaneously without sacrificing speed or efficiency. Its compact and lightweight design makes it easy to carry, while its reliable performance ensures your devices are powered up wherever you are. Whether you're at home, in the office, or abroad, the Porodo TerraCharge provides fast and efficient charging for a wide range of gadgets, offering a versatile and reliable solution for modern charging needs.

## Specifications

Input	100-240V, 60/50Hz, 1.3A Max
USB-C Output	5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A, 65W Max
PPS Output	5-20V/3A
USB-A Output	5V/3A, 9V/3A, 12V/2.25A, 20V/1.35A, 27W
Plug Types	EU, UK & US
Cable Included	1M 60W USB-C to USB-C Cable
Product Size	14.7 x 46.2 x 84mm
Model Number	FWC087

## Key Features

- 1. Advanced GaN Technology:** The Porodo TerraCharge utilizes cutting-edge Gallium Nitride (GaN) technology, which provides superior efficiency compared to

traditional silicon-based adapters. This enables faster charging speeds, reduced heat output, and a more compact design, making it a high-performance option for modern devices.

**2. Dual-Port Charging:** With two USB ports, this adapter allows you to charge two devices simultaneously, ensuring you stay connected and powered up without the need for multiple chargers. Whether it's your smartphone, tablet, or other gadgets, the TerraCharge keeps everything running smoothly.

**3. High-Power Output:** Delivering a robust 65W of charging power, the TerraCharge is capable of quickly charging a variety of devices, including laptops, smartphones, and more. It's designed to meet the power needs of high-demand electronics, providing reliable performance in any setting.

**4. Interchangeable Plugs for Global Compatibility:** Featuring interchangeable plugs for the US, UK, and EU, this adapter is tailored for international use. No matter where you're traveling, the TerraCharge ensures you can always power your devices without the hassle of carrying multiple adapters.

**5. Compact and Travel-Friendly Design:** Its sleek, lightweight build makes it perfect for travel. The Porodo TerraCharge is easy to pack, take with you, and store, all while delivering powerful, efficient charging whenever and wherever you need it.

**6. Global Travel Ready:** Designed with portability in mind, this adapter is the ideal charging companion for globetrotters. The versatile plug system and compact size ensure you can stay charged in any part of the world, making it a must-have for both business and leisure trips

## Usage Instructions

### **1. Plug Installation:**

**1.1** Choose the appropriate plug type (US, UK, or EU) for your region by aligning it with the adapter's slot.

**1.2** Firmly insert the selected plug into the adapter, ensuring it clicks securely into place.

### **2. Connecting Devices:**

**2.1** Plug the TerraCharge adapter into a wall outlet or power strip.

**2.2** Using the included USB-A or USB-C cables, connect your devices to the available USB ports on the adapter. Both ports can be used simultaneously to charge multiple devices.

### **3. Charging Your Devices:**

**3.1** Once connected, your devices will begin charging automatically. The adapter's 65W power output ensures fast and efficient charging.

**3.2** The adapter is designed to optimize power delivery for a variety of devices, including smartphones, tablets, and laptops.

## **Safety Precautions**

**1. Use with Compatible Devices:** Ensure that the devices you connect to the TerraCharge adapter are within the power limits of the 65W output. Avoid plugging in devices that require more power than the adapter can provide.

**2. Proper Plug Insertion:** Always insert the plug into the wall outlet or power strip fully and securely. Do not use the adapter if the plug is damaged or does not fit properly.

**3. Avoid Overloading:** Do not connect more than two devices simultaneously if they exceed the total 65W power output. Overloading the adapter could cause overheating or damage to your devices.

**4. Monitor Heat Levels:** While GaN technology helps reduce heat, the adapter may still generate some warmth during use. If the adapter becomes excessively hot, unplug it immediately and allow it to cool down before reconnecting.

**5. Keep Away from Water:** Keep the adapter and its cables away from moisture or water sources. Do not use the adapter if it is wet or exposed to liquid, as this could result in electrical shock or damage.

**6. Use in Dry Environments:** Only use the adapter in dry, cool environments. Avoid exposing it to high humidity or extreme temperatures to prevent damage and ensure safe operation.

**7. Cable Safety:** Always inspect the USB cables for signs of damage before use. Do not use frayed or damaged cables, as they could cause short circuits or electrical hazards.

8. **Unplug When Not in Use:** To conserve energy and maintain safety, unplug the adapter from the wall outlet when not in use. This also prevents unnecessary wear on the adapter.
9. **Proper Storage:** Store the adapter in a safe, dry place when not in use. Avoid placing it in areas where it could be exposed to high pressure, physical shock, or heavy objects.
10. **Do Not Disassemble:** The adapter should not be disassembled, modified, or repaired by unauthorized personnel. Any attempt to open or modify the unit may void the warranty and cause safety risks.

## **Disposal**

This product must not be disposed of as unsorted household waste. It is important to separate such waste for proper treatment and recycling, in compliance with local waste management regulations.



## **Warranty**

Products that you buy directly from our **Porodo** website or shop come with a 24-month warranty.

When you buy **Porodo** products from any of our approved sellers, you only get a 12-month warranty. If you want to extend this warranty, go to our website at **porodo.net/warranty** and fill out the form with your information. Don't forget to upload a picture of the product too. After we've checked and accepted your request, we'll send you an email to confirm that your product's warranty has been extended.

For more info, please check:  
**porodo.net/warranty**

## **Contact Us**

If you have any questions about this Privacy Policy, please contact us at:

**info@porodo.net**

Website: **porodo.net**

Service Support: **support@porodo.net**

Instagram: **porodo**